

# Technical Specifications

<b>Model m492k</b>	<b>DT099A</b>
<b>Processor &amp; Speed</b>	2.8HT GHz/800 Intel® Pentium® 4 Processor – PGA478
<b>Chipset</b>	Intel® 865G
<b>Motherboard</b>	Cobra-GL6E (4PSD-LA)
<b>RAM</b>	512/3200 MB 400DDR SDRAM (2x256)
Maximum	4 GB (4x1024MB DDR SDRAM)
Sockets	Four 184-pin DDR DIMMs
Size	128, 256, 512 AND 1024 MB DDR DIMMs
<b>Free DIMM Sockets</b>	Two
Pairs Required	No
Type Supported	JEDEC unbuffered DDR SDRAM DIMM specification
<b>Cache</b>	8KB Data Cache + Trace Cache L1, 512 KB L2 Integrated on Processor module
<b>Hard Drive</b>	120 GB (7200 RPM)
<b>Optical Drive</b>	CD-RW/DVD-ROM Drive 48x24x16x48 48X- Write /24X - Re-write /16x- DVD Read 48X - CD-ROM Read
Average Random Access	DVD =115ms / CD-ROM =95ms
Transfer Rate	DVD = 21.6/sec. / CD-ROM = 7.2MB/sec.
<b>Diskette Drive</b>	3.5" (1.44MB)
<b>7 in 1 Card Reader</b>	Compact Flash I/II; Memory Stick/Pro; MMC/SD; Smart Media
<b>Video Graphics</b>	AGP 8X Graphics Card
Controller	ATI R9200
Video Memory	128 MB DDR, not upgradeable
Video Connectors	Composite & S-Video - NTSC
<b>TV-Tuner</b>	TV-Tuner w/FM Capture Card
<b>Network Card</b>	10/100 BaseT, Integrated
<b>1394 Card</b>	IEEE-1394, Integrated
<b>Sound</b>	AC'97, 6 Channel, Integrated on MB
Controller	Realtek ALC650
<b>Chassis</b>	Everest3, 230 PSU
<b>USB Interface Specification</b>	USB 2.0
<b>External Ports</b>	6= USB, 1= serial, 1= parallel, 2=1394
Front I/O Connector	2= USB, 1= 1394; 7 in 1 Card Reader; 1= Microphone; 1=Line In; 1=Headphone; Video/S-Video In
<b>Expansion Slots (Total)</b>	3= PCI, 1= AGP
<b>Expansion Slots (FREE)</b>	2= PCI
<b>Drive Bays (Total)</b>	Two 5.25" external, One 3.5" external, Two 3.5" internal
<b>Drive Bays (FREE)</b>	One 5.25" external, One 3.5" external, One 3.5" internal
<b>Keyboard/Mouse</b>	HP Wireless Internet command center; One-touch Internet keyboard, Wireless optical scrolling mouse

---

Copyright Hewlett-Packard Co. 1994-2003  
 This information is subject to change without notice and  
 is provided "as is" with no warranty.  
 Hewlett-Packard shall not be liable for any direct,  
 indirect, special, incidental or consequential damages  
 in connection with the use of this material.